

PUBLIC ADDRESS / PUBLIC ADDRESS AMPLIFIERS / MASTER

MA-400RGUZ

PA AMPLIFIER USB/SD/FM



DESCRIPTION

PA amplifier with USB/SD recorder/player and FM radio

BENEFITS

Versatile and complete equipment integrating all the necessary elements of a professional sound installation: microphone and line inputs, auxiliary input, USB/SD recorder/player, FM radio, mixer and amplifier. Designed for use in PA installations with 100 V line speakers or mono installations with low impedance speakers. Speaker zone selector. Audio inputs with market standard connections: XLR, jack, RCA and euroblock. Speaker connectors with screw terminals, secure and easy to connect. High power and sound quality.

APPLICATIONS

PA and background music installations with 100 V or low impedance line loudspeakers. Commercial premises, educational centres, monuments, exhibitions, bars, restaurants, etc.

TECHNICAL DATA

400 W RMS
Microphone inputs with volume control
5 selectable speaker zones
Priority paging
Tone controls
100 V, 70 V and low impedance outputs



Expand product information on:
<https://fonestar.com/es/MA-400RGUZ>

TECHNICAL CHARACTERISTICS

FEATURES	PA amplifier. USB/SD recorder/player. Digital FM radio tuner. 5 selectable loudspeaker zones. Phantom power supply. Priority paging. Alert chimes. Siren. Echo effect.
POWER	450 W maximum, 400 W RMS
RESPONSE	50-17,000 Hz ± 3 dB
DISTORTION	Harmonic: < 0.5%
INPUTS	4 balanced mics/lines, combo (XLR and 6.3 mm jack) 600 Ohm/47,000 Ohm 3 mV RMS/300 mV RMS, 10 mV RMS/1 V RMS and euroblock 3 mV RMS/300 mV RMS 2 aux, 2 x RCA and euroblock 47,000 Ohm 700 mV RMS 1 amp in, RCA 10,000 Ohm 1 V RMS 1 tel. input, 600 Ohm 320 mV euroblock
OUTPUTS	1 line out, 2 x RCA 47,000 Ohm 500 mV RMS 1 pre out, RCA 600 Ohm 1 V RMS
CONTROLS	Tone: Bass: ± 10 dB Treble: ± 10 dB Volume: 1 to 4 aux inputs, general volume and USB/SD player
PLAYER	USB/SD recorder/player and digital FM tuner with presets and auto scan
PHANTOM	48 V in mics 1 to 4, selectable
PRIORITY	Chimes for paging and siren button and contact closure Tel. input via signal level Input 1 via signal level, selectable
ZONE SELECTOR	5 selectable loudspeaker zones
IMPEDANCE	4, 8 and 16 Ohm and 100 and 70 V line, screw terminals
POWER SUPPLY	230/115 V AC, 900 W
DIMENSIONS	482 x 133 x 480 mm depth. 3 U 19" rack



Expand product information on:
<https://fonestar.com/es/MA-400RGUZ>

WEIGHT	17.4 kg
ACCESSORIES	Antenna cable



Expand product information on:
<https://fonestar.com/es/MA-400RGUZ>